

CLAIMSWhat is claimed is:

1. A pool controller system for distributing line voltage from a line voltage service to one or more line voltage loads and controlling operation of a pool service system, comprising:

5 a housing;

10 a controller circuit board assembly mounted within the housing, including a plurality of line voltage output terminals for connection to respective line voltage loads via line voltage wiring connections, a set of circuit board line voltage contact surfaces, a plurality of circuit conductors for providing circuit connections between the contact surfaces and respective ones of the line voltage output terminals, wherein the controller circuit board assembly routes line voltage from the circuit board line voltage contact surfaces to the output terminals;

15 a terminal connector structure mounted within the housing, said connector structure having a set of line voltage connectors, each line voltage connector including a pressure connector for pressure connection of a corresponding set of line voltage service conductors and a connector line voltage contact surface for contacting a board line voltage contact surface;

20 removable fastening structures for securing the board assembly in position within the housing such that each of the circuit board line voltage contact surfaces is in intimate electrical contact with a corresponding connector line voltage contact surfaces, and for permitting the board assembly to be removed for repair or replacement without disconnecting the line voltage supply conductors from said pressure connectors.

25

30

2. The system of Claim 1 further including:

a plurality of sets of line voltage conductors for connections from the circuit board assembly to the respective plurality of line voltage loads; and

5 at least one line voltage connector structure for removable connection of the plurality of sets of line voltage conductors to corresponding ones of the line voltage output terminals, wherein the sets of line voltage conductors can be readily connected and disconnected from the board assembly by use of the connector structure.

3. The system of Claim 1 further comprising a voltage transformer for transforming the line voltage to low voltage levels, and wherein the board assembly includes:

5 a plurality of low voltage terminals for connection to low voltage wiring running to low voltage devices;

10 at least one low voltage connector structure for removable connection of said low voltage wiring, wherein the low voltage wiring can be readily connected and disconnected from the board assembly by use of the low voltage connector structure.

4. The system of Claim 1 wherein the board assembly further includes a plurality of non-resettable circuit protection devices for providing circuit protection for the line voltage loads.

5. The controller system of Claim 4, wherein the circuit protection devices include fuse devices mounted on the printed wiring board.

6. The controller system of Claim 1, wherein the circuit board assembly includes a prefabricated printed wiring board including conductor traces, and the plurality

of circuit conductors are defined by a set of said circuit traces.

5 7. The controller system of Claim 1, wherein said line voltage supply is a line voltage supply having a neutral conductor, a first phase conductor and a second phase conductor, and the first phase conductor and the second phase conductor are connected by a corresponding one of said pressure connectors.

8. The controller system of Claim 1, further comprising:

5 a voltage transformer mounted within the cabinet housing for transforming line voltage to low voltage; and wherein the controller circuit board assembly further includes a plurality of low voltage switches for selectively applying low voltage to respective low voltage output wiring connections.

5 9. The controller system of Claim 1, wherein the cabinet housing defines a main compartment and a plurality of secondary compartments, the main compartment having routed therein all line voltage wiring entering the cabinet, the secondary compartments being shielded from the main compartment and having routed therein only low voltage wiring carrying low voltage signals.

10. The controller system of Claim 9, wherein the main compartment is separated from the plurality of secondary compartments by conductive inner wall structures.

11. A method for installing a pool controller system in a pool service system including one or more line voltage loads, comprising:

5 providing a pool controller circuit board assembly,
the assembly including a plurality of line voltage output
terminals for connection to respective line voltage loads
via line voltage wiring connections, a set of circuit board
line voltage contact surfaces, a plurality of circuit
conductors for providing circuit connections between the
10 contact surfaces and respective ones of the line voltage
output terminals, wherein the controller circuit board
assembly routes line voltage from the circuit board line
voltage contact surfaces to the output terminals;

15 providing a terminal connector structure, said
connector structure having a set of line voltage
connectors, each line voltage connector including a
pressure connector for pressure connection of a
corresponding set of line voltage service conductors and a
connector line voltage contact surface for contacting a
20 board line voltage contact surface;

mounting the terminal connector structure within a
housing;

25 connecting the set of line voltage service conductors
to the terminal connector structure with the pressure
connectors;

30 securing the board assembly in position within the
housing with removable fastening structures such that each
of the circuit board line voltage contact surfaces is in
intimate electrical contact with a corresponding connector
line voltage contact surfaces.

12. The method of Claim 11 further including:

providing a plurality of sets of line voltage
conductors for connections from the circuit board assembly
to the respective plurality of line voltage loads;

5 connecting the plurality of sets of line voltage
conductors to corresponding ones of the line voltage output

10055555-020402

terminals by at least one line voltage connector structure, wherein the sets of line voltage conductors can be readily disconnected from the board assembly by use of the connector structure.

13. The method of Claim 11 wherein the board assembly includes a plurality of low voltage terminals for connection to low voltage wiring running to low voltage devices, the method further comprising:

connecting the low voltage terminals to the low voltage wiring using at least one low voltage connector structure for removable connection of said low voltage wiring, wherein the low voltage wiring can be readily connected and disconnected from the board assembly by use of the low voltage connector structure.

14. A pool controller system for distributing line voltage from a line voltage service to one or more line voltage loads and controlling operation of a pool service system, comprising:

a housing, comprising a main compartment and a plurality of secondary compartments;

a controller circuit board assembly mounted within the main compartment of the housing, including an electronic controller, a plurality of line voltage output terminals for connection to respective line voltage loads via line voltage wiring connections, a plurality of low voltage terminals for connection to respective low voltage devices, a set of circuit board line voltage contact surfaces, a plurality of circuit conductors for providing circuit connections between the contact surfaces and respective ones of the line voltage output terminals, wherein the controller circuit board assembly routes line voltage from the circuit board line voltage contact surfaces to the

output terminals, and routes low voltage signals between
20 low voltage circuitry on the circuit board, the controller
and the low voltage terminals;

a plurality of line voltage supply conductors passed
into the main compartment of the housing from a line
voltage supply source;

25 a plurality of sets of line voltage load conductors
passed into the main compartment of the housing from said
plurality of line voltage loads and connected to the
circuit board assembly;

30 a plurality of sets of low voltage conductors
connected to respective low voltage devices, the sets of
low voltage connected routed from respective ones of the
secondary compartments into the main compartment for
connection to the circuit board assembly;

35 wherein no conductors carrying line voltage are routed
into any of the plurality of secondary compartments.

15. The system of Claim 14 wherein:

the line voltage supply is a 240 VAC line voltage
supply;

5 at least one of said line voltage loads is a 240 VAC
load; and

at least one of the line voltage loads is a 120 VAC
load.

16. A method for providing line voltage to a
plurality of line loads for a bathing pool installation,
comprising:

5 connecting a line voltage supply at a line voltage
distribution panel to a ground fault circuit interrupter
(GCFI), the line voltage having a sufficient power rating
to supply power for said plurality of loads;

providing a pool control panel including a pool controller circuit assembly, the assembly including a circuit protection device and an electrical switching device for each of said plurality of line voltage loads, a wiring circuit to distribute line voltage through the respective circuit protection devices and circuit protection devices to line voltage load terminal connections at the controller circuit assembly, and an electronic controller coupled to each of the switching devices for actuating each of said switching devices;

providing a GFCI-protected line voltage connection between the GFCI and the controller circuit assembly; and

electrically connecting each of said plurality of line voltage loads to a corresponding terminal connection at said controller circuit assembly.

17. The method of Claim 16 wherein the circuit protection devices include fuse protection devices.

18. The method of Claim 16 wherein the switching devices include switching relays.

19. The method of Claim 16 wherein:

the line voltage supply is a 240 VAC line voltage supply;

at least one of said line voltage loads is a 240 VAC load; and

at least one of the line voltage loads is a 120 VAC load.

20. In a bathing or swimming pool installation, including a pool water holding structure, a method for releasing water into the water holding structure, comprising:

5 providing a valve connected to a water supply line,
the valve responsive to valve control signals to open and
close, wherein the valve in an open state releases water
from the water supply line into the water holding
10 structure, and in a closed state prevents water from
flowing from the water supply line into the water holding
structure;

providing an electronic control system responsive to
a user commands through a control panel to generate the
valve control signals;

15 entering a user command through the control panel to
actuate the valve;

opening the valve in response to the user command;
automatically closing the valve after a predetermined
time has elapsed after opening the valve.

21. The method of Claim 20 further comprising:
setting the predetermined time during a programming
mode.

22. The method of Claim 21 further comprising:
storing in an electronic memory a time value
corresponding to the predetermined time.

23. The method of Claim 20 further comprising:
automatically closing the valve if the water level
reaches an overflow level during the predetermined time
interval.

24. In a bathing or swimming pool installation,
including a pool water holding structure and a pool control
system, a method for automatically releasing water into the
water holding structure, comprising:

5

10

15

20

1. 2. 3. 4. 5. 6. 7. 8. 9. 10. 11. 12. 13. 14. 15. 16. 17. 18. 19. 20. 21. 22. 23. 24. 25. 26. 27. 28. 29. 30. 31. 32. 33. 34. 35. 36. 37. 38. 39. 40. 41. 42. 43. 44. 45. 46. 47. 48. 49. 50. 51. 52. 53. 54. 55. 56. 57. 58. 59. 60. 61. 62. 63. 64. 65. 66. 67. 68. 69. 70. 71. 72. 73. 74. 75. 76. 77. 78. 79. 80. 81. 82. 83. 84. 85. 86. 87. 88. 89. 90. 91. 92. 93. 94. 95. 96. 97. 98. 99. 100. 101. 102. 103. 104. 105. 106. 107. 108. 109. 110. 111. 112. 113. 114. 115. 116. 117. 118. 119. 120. 121. 122. 123. 124. 125. 126. 127. 128. 129. 130. 131. 132. 133. 134. 135. 136. 137. 138. 139. 140. 141. 142. 143. 144. 145. 146. 147. 148. 149. 150. 151. 152. 153. 154. 155. 156. 157. 158. 159. 160. 161. 162. 163. 164. 165. 166. 167. 168. 169. 170. 171. 172. 173. 174. 175. 176. 177. 178. 179. 180. 181. 182. 183. 184. 185. 186. 187. 188. 189. 190. 191. 192. 193. 194. 195. 196. 197. 198. 199. 200. 201. 202. 203. 204. 205. 206. 207. 208. 209. 210. 211. 212. 213. 214. 215. 216. 217. 218. 219. 220. 221. 222. 223. 224. 225. 226. 227. 228. 229. 230. 231. 232. 233. 234. 235. 236. 237. 238. 239. 240. 241. 242. 243. 244. 245. 246. 247. 248. 249. 250. 251. 252. 253. 254. 255. 256. 257. 258. 259. 260. 261. 262. 263. 264. 265. 266. 267. 268. 269. 270. 271. 272. 273. 274. 275. 276. 277. 278. 279. 280. 281. 282. 283. 284. 285. 286. 287. 288. 289. 290. 291. 292. 293. 294. 295. 296. 297. 298. 299. 300. 301. 302. 303. 304. 305. 306. 307. 308. 309. 310. 311. 312. 313. 314. 315. 316. 317. 318. 319. 320. 321. 322. 323. 324. 325. 326. 327. 328. 329. 330. 331. 332. 333. 334. 335. 336. 337. 338. 339. 340. 341. 342. 343. 344. 345. 346. 347. 348. 349. 350. 351. 352. 353. 354. 355. 356. 357. 358. 359. 360. 361. 362. 363. 364. 365. 366. 367. 368. 369. 370. 371. 372. 373. 374. 375. 376. 377. 378. 379. 380. 381. 382. 383. 384. 385. 386. 387. 388. 389. 390. 391. 392. 393. 394. 395. 396. 397. 398. 399. 400. 401. 402. 403. 404. 405. 406. 407. 408. 409. 410. 411. 412. 413. 414. 415. 416. 417. 418. 419. 420. 421. 422. 423. 424. 425. 426. 427. 428. 429. 430. 431. 432. 433. 434. 435. 436. 437. 438. 439. 440. 441. 442. 443. 444. 445. 446. 447. 448. 449. 450. 451. 452. 453. 454. 455. 456. 457. 458. 459. 460. 461. 462. 463. 464. 465. 466. 467. 468. 469. 470. 471. 472. 473. 474. 475. 476. 477. 478. 479. 480. 481. 482. 483. 484. 485. 486. 487. 488. 489. 490. 491. 492. 493. 494. 495. 496. 497. 498. 499. 500. 501. 502. 503. 504. 505. 506. 507. 508. 509. 510. 511. 512. 513. 514. 515. 516. 517. 518. 519. 520. 521. 522. 523. 524. 525. 526. 527. 528. 529. 530. 531. 532. 533. 534. 535. 536. 537. 538. 539. 540. 541. 542. 543. 544. 545. 546. 547. 548. 549. 550. 551. 552. 553. 554. 555. 556. 557. 558. 559. 560. 561. 562. 563. 564. 565. 566. 567. 568. 569. 570. 571. 572. 573. 574. 575. 576. 577. 578. 579. 580. 581. 582. 583. 584. 585. 586. 587. 588. 589. 590. 591. 592. 593. 594. 595. 596. 597. 598. 599. 600. 601. 602. 603. 604. 605. 606. 607. 608. 609. 610. 611. 612. 613. 614. 615. 616. 617. 618. 619. 620. 621. 622. 623. 624. 625. 626. 627. 628. 629. 630. 631. 632. 633. 634. 635. 636. 637. 638. 639. 640. 641. 642. 643. 644. 645. 646. 647. 648. 649. 650. 651. 652. 653. 654. 655. 656. 657. 658. 659. 660. 661. 662. 663. 664. 665. 666. 667. 668. 669. 670. 671. 672. 673. 674. 675. 676. 677. 678. 679. 680. 681. 682. 683. 684. 685. 686. 687. 688. 689. 690. 691. 692. 693. 694. 695. 696. 697. 698. 699. 700. 701. 702. 703. 704. 705. 706. 707. 708. 709. 710. 711. 712. 713. 714. 715. 716. 717. 718. 719. 720. 721. 722. 723. 724. 725. 726. 727. 728. 729. 730. 731. 732. 733. 734. 735. 736. 737. 738. 739. 740. 741. 742. 743. 744. 745. 746. 747. 748. 749. 750. 751. 752. 753. 754. 755. 756. 757. 758. 759. 760. 761. 762. 763. 764. 765. 766. 767. 768. 769. 770. 771. 772. 773. 774. 775. 776. 777. 778. 779. 780. 781. 782. 783. 784. 785. 786. 787. 788. 789. 790. 791. 792. 793. 794. 795. 796. 797. 798. 799. 800. 801. 802. 803. 804. 805. 806. 807. 808. 809. 810. 811. 812. 813. 814. 815. 816. 817. 818. 819. 820. 821. 822. 823. 824. 825. 826. 827. 828. 829. 830. 831. 832. 833. 834. 835. 836. 837. 838. 839. 840. 84

5

10

15

11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000 1001 1002 1003 1004 1005 1006 1007 1008 1009 1010 1011 1012 1013 1014 1015 1016 1017 1018 1019 1020 1021 1022 1023 1024 1025 1026 1027 1028 1029 1030 1031 1032 1033 1034 1035 1036 1037 1038 1039 1040 1041 1042 1043 1044 10

5

pressure sensing apparatus for sensing a filter back-pressure and providing filter pressure signals; and

5

one or more electrically powered devices associated with operation of the spa or pool;

a ground fault circuit interrupter (GFCI) circuit;

10

to detect ground faults and interrupt the service upon detection of a ground fault;

15 a manually actuated low voltage emergency switch system mounted in the vicinity of the spa or pool, the switch system connected to the controller system and to a ground fault test circuit, the test circuit inducing a ground fault between line voltage and ground upon activation by the emergency switch system, thereby tripping the GFCI circuit.

31. The control system of Claim 30, wherein the controller system includes a monitoring system for detecting the presence of the emergency switch system and taking a predetermined action in the event the emergency switch system is not detected.

32. The control system of Claim 30 wherein the predetermined action includes interrupting line voltage to the devices.

33. The control system of Claim 30 wherein the predetermined action includes generating an audible or visual warning signal indicating that the emergency switch system has not been detected.

34. The control system of Claim 30 wherein the emergency switch system includes a normally open manually activated switch, and the monitoring system includes a resistive element connected in parallel with the switch, a circuit for providing a low voltage across the resistive element, and a voltage monitoring circuit for monitoring a voltage on the emergency switch system, wherein the control system is responsive to signals provided by the monitoring

system to determined whether the emergency switch system is properly installed.

35. A spa or pool system, comprising:

a gas-fired heater for heating water circulated into the spa or pool, the heater connected to a source of gas fuel through a gas input line;

a gas pressure sensor coupled to gas input line to detect the gas pressure level, the sensor providing a gas pressure sensor signal;

a controller system operatively connected to the heater for controlling the operation of the heater, the controller system responsive to the gas pressure sensor signal to take a predetermined action in the event the sensor signal indicates that the gas pressure is below a predetermined gas pressure threshold value.

36. The system of Claim 35, wherein the predetermined action includes generating an audible or visual warning signal.

37. The system of Claim 35 wherein the predetermined action includes disabling the heater from operation.

38. In a pool/spa service system including an electronic controller, the controller receiving electrical power from a line voltage powered circuit, and including a ground fault interrupt circuit (GFCI) for interrupting line voltage in the event of a detected ground fault, a method for checking for proper operation and installation of the GFCI, comprising:

inducing a ground fault between line voltage and ground to check operation of the GFCI;

10 monitoring line voltage to determine whether line
voltage has been interrupted in response to the induced
ground fault;

if interruption of line voltage does not occur,
automatically taking a predetermined warning or corrective
15 action.

39. The method of Claim 38 further including
generating a warning signal indicative of failure of the
GFCI if interruption of line voltage does not occur in
response to said inducing of said ground fault.

40. The method of Claim 38 further including the step
of storing test outcome indicating data in a nonvolatile
memory in the event interruption of line voltage occurred
in response to said inducing a ground fault, said stored
5 data indicating successful completion of the GFCI test,
said storing occurring prior to shutting down operation of
the controller due to said interruption of line voltage.

41. The method of Claim 40, further comprising:
powering up the controller;
reading said nonvolatile memory to determine whether
said test outcome indicating data is stored in said memory;
5 if said test outcome indicating data is stored in
memory, operating the controller in a normal manner.

42. The method of Claim 38 wherein said step of
inducing a ground fault includes closing a controller
controlled switch to connect a resistive element from a
line voltage conductor to earth ground.

43. The method of Claim 38 wherein said step of
monitoring line voltage includes converting the line

5 voltage to a low voltage waveform of similar periodicity as the line voltage, and monitoring the low voltage waveform to detect that the waveform has been interrupted.

44. The method of Claim 38 wherein said taking said predetermined warning or corrective action includes:

providing a warning signal indicating that the GFCI is not properly connected or operational.

45. The method of Claim 38 wherein said taking said predetermined warning or corrective action includes preventing the system from operating normally.

5 46. The method of Claim 45 wherein said system includes at least one line voltage load controlled by the controller, and said preventing said system from operating normally includes preventing application of line voltage to the at least one line voltage load.

47. The method of Claim 38 wherein said method is an algorithm automatically performed by the controller.

5 48. A method for operating an electronic pool/spa controller which has control of at least one line voltage load, and wherein the line voltage which powers the load also provides primary power for the electronic controller and is protected by a ground fault circuit interrupter (GFCI), the method comprising:

applying electrical power to the controller, the electrical power resulting from the line voltage;

10 checking a nonvolatile memory for information regarding prior successful GFCI testing;

if said information is stored in said memory, proceeding to normal controller operation;

if said information is not stored in said memory, conducting a GFCI test procedure, said procedure including inducing a ground fault, determining whether line voltage is interrupted within a predetermined time period after said inducing, if line voltage is interrupted, continuing operation of the controller through a short term auxiliary power supply in order to write to said nonvolatile electronic memory said information.

49. An improved reliability temperature sensor, comprising:

a housing;

a first solid state temperature sensing device mounted in the housing;

a second solid state temperature sensing device mounted in the housing;

a first conductor circuit for making electrical connection from outside the housing to a first terminal of said first device and to a first terminal of the second device;

a second conductor circuit for making electrical connection outside the housing to a second terminal of the first device; and

a third conductor circuit for making electrical connection outside the housing to a second terminal of the second device.

49. The sensor of Claim 48 wherein said first device is a first thermistor, and said second device is a second thermistor.

50. The sensor of Claim 48 further comprising a circuit board assembly for mounting said first thermistor device and said second thermistor device, said circuit

board assembly being inserted into said housing during assembly, and a collar structure which includes a stop shoulder surface which contacts an end of said housing to control a depth of insertion of said circuit board assembly into said housing.

51. The sensor of Claim 50 wherein said first and second solid state temperature sensing devices are mounted adjacent a distal end of said circuit board assembly a predetermined distance from said distal end when said stop shoulder surface contacts said housing end.

52. The sensor of Claim 50 further comprising a potting compound disposed in said housing.

53. A method of assembling and programming a circuit board assembly for a bathing pool controller system, comprising:

providing a circuit board configured for in-circuit-programming;

populating the board with electronic circuit devices; installing an in-circuit-programmable microprocessor device on the circuit board;

connecting the board to a programmer device using electrical connections;

loading a program into a nonvolatile memory of the microprocessor device from the programmer device;

powering up the circuit board; and

verifying the proper functioning of the circuit board with the microcomputer.